

INSTALLER/CUSTOMER QUICK INSTALL GUIDE

NOTE: Be certain ports 3001 through 3017 are open on your network to permit internet access for the MTG 1250i prior to installation.

- 1) Connect the MTG 1250i to an electrical outlet.
- 2) Connect the MTG 1250i to your network router.
- 3) Launch the MTG IP Config program on the "MTG 1250i Installer Disk" provided with your unit on any computer connected to the same network router as the 1250i.
- 4) The program will begin scanning for the MTG 1250i on your network.
- 5) The MTG 1250i IP address will appear in the MTG IP Config window. Write it down.
- 6) Launch the MTG CB Config program on the "MTG 1250i Installer Disk" on the same computer connected to the network.
- 7) Enter the MTG 1250i IP address in the "Unit's IP Address"
- 8) Enter the "Unit's Password" TLKDIG
- 9) Press "Connect"
- 10) The MTG Server IP address 207.172.195.169 should appear in both the "Connect-Back IP Addresses" and "Confirm Connect-Back Addresses" fields reading IP 1. If it doesn't, please enter into each field.
- 11) Under Confirm Connect-Back IP Addresses, press "Confirm" next to the MTG Server IP Address 207.172.195.169 in field IP 1.
- 12) Once it reads "Successful!" then you're set!
- 13) Close both MTG programs.
- 14) Connect the supplied audio cable to the audio input of your phone system.
- 15) Professional MTG on hold messaging is now being played on your phone system.
- 16) You're officially minding the gap!

MTG Technical Support: 888-353-6745